# **SIEMENS**

### **Outdoor Uni-PAK All-In-One Metering**

Catalog Number

Enclosure

### Italog Number

# WPL10612RJ

Type 3R

Main Bus Rating: 1000 Amps 120/240 V~, 1 Phase, 3 Wire 208Y/120 V~, 1 Phase, 3 Wire (5th jaw may be required)

Meter Socket Rating: 200A Continuous Branch Rating:

Top breakers both sides: 200Amps Max. All other breakers: 225 Amps Max.


ierminai	wire Size	iorque
A, B, N1	See Chart Below	
N2, G	300 kcmil - #4 AWG	275 LB-IN
Equip GNE	#2/0 - 4 AWG	110 LB-IN
Lug Kit	Wire Size	Torque
H56476	800 kcmil - #3/0 AWG	500 LB-IN
H56732M		

For installation by Qualified Person in accordance with all local electrical codes and/or the National Electrical Code ®.

**Suitable Only For Use As Service Equipment.** Install no more than six main disconnecting means.

For overhead or underground service.

Use 60/75°C Copper or Aluminum Conductors for all panel terminals and on circuit breaker terminals when breakers are so marked,



Siemens Industry, Inc. Norcross, Georgia U.S.A.

D 40900526 0101 Rev.A

The National Electrical Code is a registered trademark of the National Fire Protection Association.
2011 Copyright Siemens Industry, Inc.

## **SIEMENS**

### **Outdoor Uni-PAK All-In-One Metering**

#### General Information:

Circuit breaker overload trip position is indicated by handle position midway between ON and OFF. To reset, move handle to OFF position, then turn ON,

Short Circuit Current Rating

The maximum short circuit current rating of this device is 100,000 RMS symmetrical amperes, 120/240 V∼. The actual rating is limited to the lowest interrupting rating of any circuit breaker installed. Use only Siemens type QS, QSH, QSHH, HQS, HQSH, QP, QPH, HQP, MP-T, MP-HT or MP-MT circuit breakers. Use of other circuit breakers in this device will void the warranty.

#### Accessories

Use HD Type Hubs if required		
Trade Size (in)	Catalog No.	
2"	. EC56854	
2-1/2"	EC56855	
3"	EC56856	
3-1/2"	EC56857	
4"	EC56858	
Closure Plate	FC56933S	

**Important:** Do not allow petroleum based (hydrocarbon) sprays, chemicals, solvents or any paint to contact interior components. Petroleum based chemicals can cause degradation of electrical insulating materials.

Siemens Industry, Inc. Norcross, Georgia U.S.A.

40900526 0201 Rev.A

D

© 2011 Copyright Siemens Industry, Inc.