

CATALOG NUMBER

ECLK3

electricCenter
ACCESSORIES

**Neutral Lug Kit
#1 - 300 kcmil**

Same As:

- LK3
- DLK3



INSTALLATION INSTRUCTIONS



⚠ DANGER

Hazardous Voltage.
Will cause death, serious injury
or substantial property damage.

Turn off power supplying this
equipment before working inside.



SAFETY INSTRUCTIONS

1. Turn off and lock off the power supplying the load center before working inside.
2. Remove 3 screws from neutral bar at location desired for mounting lug kit.
3. Position lug on center hole.
4. Secure lug to neutral bar with flat head screw. Torque screw to 40-50 lb.-ins.
5. Insert set screw in lug.

See wiring diagram for wire range size and tightening torque requirements.

Note: This instruction outlines the recommended installation procedure.




SET SCREW



FLAT HEAD
SCREW



LUG



© 2010 Copyright Siemens Industry, Inc.

Siemens Industry, Inc.

Norcross, Georgia U.S.A.

4810449 Rev.B

Assembled in Mexico