

Terminal

Outdoor Uni-PAK All-In-One Metering

Catalog Number

Main Bus Rating: 800 Amps

120/240 V~, 1 Phase, 3 Wire

WTGL8612RJ, WPL8612RJ

Enclosure

Type 3R Torque

2,			.0.900
120/240 V∼, 1 Phase, 3 Wire 208Y/120 V∼, 1 Phase, 3 Wire	A, B, N1	See Chart Below	
	N2, G	300 kcmil - #4 AWG	275 LB-IN
Meter Socket Rating: 200A Continuous	Equip GND	#2/0 - 4 AWG	110 LB-IN
Branch Rating:	Lug Kit	Wire Size	Torque
Top breakers both sides: 200Amps Max.	H56476	800 kcmil - #3/0 AWG	500 LB-IN
All other breakers: 225 Amps Max.	H56732M	(2) 500 kcmil - #4 AWG	375 LB-IN
For installation by Overlifted Bearing in	Terminals A, B, N1:		

Torque 3/8-16 Nuts (9/16" drive) to 250 lb.-in.

Wire Size


All other breakers: 225 Amps Max. For installation by Qualified Person in accordance with all local electrical

codes and/or the National Electrical Code ®.

Suitable Only For Use As Service Equipment, Install no more than six main disconnecting means.

For overhead or underground service.

Use 60/75°C Copper or Aluminum Conductors for all panel



Siemens Industry, Inc., Norcross, Georgia, U.S.A. 409011990101 Rev.00

® The National Electrical Code is a registered trademark of the National Fire Protection Association. © 2018 Copyright Siemens Industry, Inc.



Outdoor Uni-PAK All-In-One Metering

General Information:

Circuit breaker overload trip position is indicated by handle position midway between ON and OFF. To reset, move handle to OFF position, then turn ON.

Short Circuit Current Rating

The maximum short circuit current rating of this device is 100,000 RMS symmetrical amperes, 120/240 V~. The actual rating is limited to the lowest interrupting rating of any circuit breaker installed. Use only Siemens type QS. QSH, QSHH, HQS, HQSH, QP, QPH, HQP, HQPH, LQ, MP-T, MP-HT, or MP-MT circuit breakers. Use of other circuit breakers in this device will void the warranty.

Accessories

5th Jaw, 9 o'Clock Position S35815-2

Use HD Type Hubs if required Trade Size (in) Catalog No. 4".....H56858-2

Closure Plate H56933

Important: Do not allow petroleum based (hydrocarbon) sprays, chemicals. solvents or any paint to contact interior components. Petroleum based chemicals can cause degradation of electrical insulating materials.

Siemens Industry, Inc., Norcross, Georgia, U.S.A. D 409011990201 Rev.00

© 2018 Copyright Siemens Industry, Inc.