

CATALOG NUMBER

ECLK2

electricCenter
ACCESSORIES

Neutral Lug Kit

Wire Range: #4 - 2/0 AWG

Same As:

■ LK2 ■ ELK2 ■ DLK2



LUG KIT INSTALLATION INSTRUCTIONS



⚠ DANGER

Hazardous Voltage.
Will cause death, serious injury
or substantial property damage.

Turn off power supplying this
equipment before working inside.



SAFETY INSTRUCTIONS

Note: This instruction outlines the recommended installation procedure.

1. Turn off and lock off the power supplying this equipment before working inside.
2. Remove 3 screws from neutral bar at location desired for mounting lug kit.
3. Position lug on center hole.
4. Secure lug to neutral bar with flat head screw. Torque screw to 40-50 lb.-ins.
5. Insert set screw in lug.

See wiring diagram for wire range size and tightening torque requirements.



SET SCREW



FLAT HEAD
SCREW



LUG

