



SIEMENS


Protect your investment

SINUMERIK 840D sI/SINUMERIK 828D

Step-by-step machine registration guide

usa.siemens.com/cnc4you

Enter data into the CNC



Create the XML registration file



NCU, Drive



Servomotor



Machine control panel



USB stick for the file transfer



E-mail file to complete registration



Machine registration step-by-step

Introduction

Registering your Siemens CNC-equipped machine tool is quick and easy — and gives you peace-of-mind knowing that support is only a phone call or an e-mail away.

Your warranty period is validated with a start and end date, and a bill of materials is communicated to Siemens so we can provide the best service and support should you require them.

This guide will take you step-by-step through the process. Just follow these easy steps:

Enter the required information into the CNC

- Manufacturer (machine tool builder)
- Machine tool dealer
- End-user

Create the XML registration file

Save the XML registration file to a USB memory stick

E-mail the XML file from your PC to complete the registration

Your SINUMERIK CNC machine tool is now fully registered.

Operator panel overview

SINUMERIK 840D sI/SINUMERIK 828D

Depending upon the SINUMERIK CNC and operator panel you're using, the location of each hard-key may vary. The location of each soft-key, however, will remain the same. Pictured in the example on the right: SINUMERIK 840D sI OP12, 12-inch operator panel



Recall

This button allows you to go back to the previous screen.



Machine area

This button allows you to go to the main (home) screen of SINUMERIK Operate.



Extend key

This button allows you to advance to the next page of settings.



Menu Select / Area switchover

This button allows you to view the main soft-keys in SINUMERIK Operate.



Alpha key group

Numerical key group

Cursor key group

Control key group

USB front interface



Recall



Machine area



Extend key




Menu Select/Area switchover

Step 1


To begin the machine registration process, you will need to collect some information.

Press the Menu Select. It is a hard-key located on the SINUMERIK operator panel.




Step 2

Next, press the Diagnostics — a soft-key found in the bottom of the screen.




Step 3

In the lower-right corner, you will press the Version key.




Step 4

In the upper-right corner, you will press the Logbook key.



Step 5

Next, press Change, which is also in the upper-right corner of the screen.




Step 6

Type in the following information as it relates to your machine tool:

- Machine model name, serial number and machine type

Navigate to empty field with cursor keys.



Step 7

Continue by entering the following information:

- Manufacturer (machine tool builder)

Manu-
facturer

Navigate to empty field with cursor keys




Press the Dealer key and continue by entering the following information:

- Machine tool dealer

Dealer

Navigate to empty field with cursor keys



identSNAPSHOT Serial number of CF card: ST-P120_HOST Import data


Machine name/no. 123456
Machine type Milling

Address selection Test Manufacturer 1

Customer number 123456
Manufacturer's name Test Manufacturer 1
Street Any Street
Post code / zip code 111AAA
Location Erlangen
Country Germany
State/county Franconia
Contact Mr Manufacturer
Phone 0049 11223344
Fax 0049 44332211
Email mr@manufacturer.de
WEB address www.manufacturer.de

Manufacturer
Dealer
End user
Cancel
OK

Alarm list Messages Alarm log NC/PLC variab. Version



identSNAPSHOT Serial number of CF card: ST-P120_HOST Import data

Machine name/no. 123456
Machine type Milling

Address selection Test Dealer 1

Customer number 123456
Dealer's name Test Dealer 1
Street This Street
Post code / zip code 333CCC
Location Dublin
Country Ireland
State/county Dublin
Contact Mr Murphey
Phone 00353 98989898
Fax 00353 89898989
Email mr@murphey.ie
WEB address www.murphey.ie

Manufacturer
Dealer
End user
Cancel
OK



Alarm list Messages Alarm log NC/PLC variab. Version

Step 9

Press the End user key and continue by entering the following information:

- End-customer

Navigate to empty field with cursor keys



identSNAPSHOT Serial number of CF card: ST-P120_HOST

Machine name/no. 123456
Machine type Milling


Address selection Test User

Customer number 123456
End user name Test User
Street Other Street
Post code / zip code 444DDD
Location Cork
Country Ireland
State/county Cork
Contact Mr Finegan
Phone 00353 676767
Fax 00353 767676
Email mr@finegan.ie
WEB address www.finegan.ie


Buttons: Import data, Manufacturer, Dealer, End user, Cancel, OK

Step 10

At any time, press the corresponding soft-key to go back to the Manufacturer, Dealer or End-user screens.



Otherwise, press OK to acknowledge the data you've just entered and continue.



identSNAPSHOT Serial number of CF card: ST-P120_HOST

Machine name/no. 123456
Machine type Milling


Address selection Test User

Customer number 123456
End user name Test User
Street Other Street
Post code / zip code 444DDD
Location Cork
Country Ireland
State/county Cork
Contact Mr Finegan
Phone 00353 676767
Fax 00353 767676
Email mr@finegan.ie
WEB address www.finegan.ie

Buttons: Import data, Manufacturer, Dealer, End user, Cancel, OK


Step 11

Press the Startup complete key.



Step 12


Confirm the Logbook entry by pressing OK.



Step 13


You're almost finished.

Press the Machine installed key.




Step 14

The information appearing on this screen should be correct. Please note that the time /time-zone may vary.




Press OK to acknowledge the information you've entered and continue.




Step 15

Next, press the Back key to return to the previous screen and to save your data.




Step 16

Now you should see a series of green check marks indicating that everything is okay.




Press the Save key.




Step 17

Insert a USB stick into the USB port located on the front of the operator panel.

Using the cursor keys, navigate to USB.



Press the OK key.





Step 18

Enter the following information, when prompted:

- Filename of this registration (required)
- Comment (optional)


Select .XML and then press OK.

This will save your new registration file to the USB stick.



Step 19

This is the screen you will see as the .XML file is being saved to your USB stick.



Step 20

Lastly, remove the USB stick and insert it into your PC.

To complete your machine registration, e-mail the .XML file to:

cncmachineregistrations.industry@siemens.com



Siemens Industry, Inc.
390 Kent Avenue
Elk Grove Village, IL 60007
1-800-879-8079

Order No. MBBR-MRGXX-0815
Printed in USA
© 2015 Siemens Industry, Inc.

The information provided in this brochure contains merely general descriptions or characteristics of performance which in case of actual use do not always apply as described or which may change as a result of further development of the products. An obligation to provide the respective characteristics shall only exist if expressly agreed in the terms of contract.

All product designations may be trademarks or product names of Siemens AG or supplier companies whose use by third parties for their own purposes could violate the rights of the owners.

usa.siemens.com/cnc

